# Expansion Module – 4 digital outputs

Version 1.0 — 02/01/2014

CE

**User Manual** 





**User Manual** 

Thank you for choosing our product.

This manual will help you with proper support and proper operation of the device.

The information contained in this manual have been prepared with utmost care by our professionals and serve as a description of the product without incurring any liability for the purposes of commercial law.

This information does not release you from the obligation of own judgment and verification.

We reserve the right to change product specifications without notice.

Please read the instructions carefully and follow the recommendations contained therein.



WARNING!

Failure to follow instructions can result in equipment damage or impede the use of the hardware or software.

Expansion Module- 4 digital outputs

#### 1. Safety rules

- Before first use, refer to this manual
- Before first use, make sure that all cables are connected properly
- Please ensure proper working conditions, according to the device specifications (eg: supply voltage, temperature, maximum power consumption)
- Before making any modifications to wiring connections, turn off the power supply

#### 2. Module Features

#### 2.1. Purpose and description of the module

4DO Module is an innovative device that provides a simple and cost-effective extension of the number of outputs in popular PLCs.

This module is connected to the RS485 bus with twisted-pair wire. Communication is via MODBUS RTU or MODBUS ASCII. The use of 32-bit ARM core processor provides fast processing and quick communication. The baud rate is configurable from 2400 to 115200.

The module is designed for mounting on a DIN rail in accordance with DIN EN 5002.

The module is equipped with a set of LEDs used to indicate the status of inputs and outputs useful for diagnostic purposes and helping to find errors.

Module configuration is done via USB by using a dedicated computer program. You can also change the parameters using the MODBUS protocol.

## 2.2. Technical Specifications

Dowor Supply	Voltage	12-24 V DC ± 20%	
Fower Supply	Maximum Current*	69 mA @ 12V / 38 mA @ 24V	
	No of outputs	4	
Digital Outpute	Max Voltage	55V	
Digital Outputs	Max current	250mA	
	Output Type	PNP	
Tomporatura	Work	-20 °C - +65°C	
remperature	Storage	-40 °C - +85°C	
	Power Supply	3 pin	
Connectore	Communication	3 pin	
Connectors	Outputs	2 x 3 pin	
	Configuration	Mini USB	
Size	Height	90 mm	
	Length	56 mm	
	Width	17 mm	
Interface	RS485	Up to 128 devices	

<sup>\*</sup> Maximum current with active Modbus transmission, all outputs on and high state on all inputs

#### 2.3. Dimensions of the product

Look and dimensions of the module are shown below. The module is mounted directly to the rail in the DIN industry standard.



### 3. Communication configuration

### 3.1. Grounding and shielding

In most cases, IO modules will be installed in an enclosure along with other devices which generate electromagnetic radiation. Examples of these devices are relays and contactors, transformers, motor controllers etc. This electromagnetic radiation can induce electrical noise into both power and signal lines, as well as direct radiation into the module causing negative effects on the system. Appropriate grounding, shielding and other protective steps should be taken at the installation stage to prevent these effects. These protective steps include control cabinet grounding, module grounding, cable shield grounding, protective elements for electromagnetic switching devices, correct wiring as well as consideration of cable types and their cross sections.

#### 3.2. Network Termination

Transmission line effects often present a problem on data communication networks. These problems include reflections and signal attenuation.

To eliminate the presence of reflections from the end of the cable, the cable must be terminated at both ends with a resistor across the line equal to its characteristic impedance. Both ends must be terminated since the direction of propagation is bidirectional. In the case of an RS485 twisted pair cable this termination is typically  $120 \Omega$ .

Expansion Module- 4 digital outputs

5/11

## 3.3. Types of Modbus Registers

There are 4 types of variables available in the module

Туре	Beginning address	Variable	Access	Modbus Command
1	00001	Digital Outputs	Bit Read & Write	1, 5, 15
2	10001	Digital Inputs	Bit Read	2
3	30001	Input Registers	Registered Read	3
4	40001	Output Registers	Registered Read & Write	4, 6, 16

## 3.4. Communication settings

The data stored in the modules memory are in 16-bit registers. Access to registers is via MODBUS RTU or MODBUS ASCII.

## **3.4.1. Default settings**

Parameter Name	Value
Address	1
Baud rate	19200
Parity	No
Data bits	8
Stop bits	1
Reply Delay [ms]	0
Modbus Type	RTU

## **3.4.2.** Configuration registers

Modbus	Dec	Hex	Nomo	Values	
Address			Name	values	
40003	2	0x02	Baud rate	0 - 2400 1 - 4800 2 - 9600 3 - 19200 4 - 38400 5 - 57600 6 - 115200 other - value * 10	
40005	4	0x04	Parity	0 – none 1 – odd 2 – even 3 – always 1 4 – always 0	
40004	3	0x03	Stop Bits LSB	1 – one stop bit 2 – two stop bits	
40004	3	0x03	Data Bits MSB	7 – 7 data bits 8 – 8 data bits	
40006	5	0x05	Response delay	Time in ms	
40007	6	0x06	Modbus Mode	0 – RTU 1 – ASCII	

### 4. Indicators



Indicator	Description
ON	LED indicates that the module is correctly powered.
TX	The LED lights up when the unit received the correct packet and sends the answer.
1, 2, 3, 4	LED indicates that the output is on.

**User Manual** 

### 5. Block diagram



## 6. Module Connection



#### **Output connection (PNP)**

## 7. Modules Registers

# 7.1. Registered access

Modbus	Dec	Hex	Register Name	Access	Description
30001	0	0x00	Version/Type	Read	Version and Type of the device
30002	1	0x01	Address	Read	Module address
40003	2	0x02	Baud rate	Read & Write	RS485 baud rate
40004	3	0x03	Stop Bits & Data Bits	Read & Write	No of Stop bits & Data Bits (see 3.4.2)
40005	4	0x04	Parity	Read & Write	Parity bit
40006	5	0x05	Response Delay	Read & Write	Response delay in ms
40007	6	0x06	Modbus Mode	Read & Write	Modbus Mode (ASCII or RTU)
40009	8	0x08	Watchdog	Read & Write	Watchdog
40013	12	0x0C	Default Output State	Read & Write	Default output state (after power on or watchdog reset)
40033	32	0x20	Received packets MSB	Read & Write	No of reactived packets
40034	33	0x21	Received packets LSB	Read & Write	No of received packets
40035	34	0x22	Incorrect packets MSB	Read & Write	No of reactived peakets with orrer
40036	35	0x23	Incorrect packets LSB	Read & Write	No of received packets with error
40037	36	0x24	Sent packets MSB	Read & Write	No of continent to
40038	37	0x25	Sent packets LSB	Read & Write	No or seril packets
40052	51	0x33	Outputs	Read & Write	Output state

## 7.2. Bit access

Modbus Address	Dec Address	Hex Address	Register name	Access	Description
193	192	0x0C0	Default state of output 1	Read & Write	Default state of output 1
194	193	0x0C1	Default state of output 2	Read & Write	Default state of output 2
195	194	0x0C2	Default state of output 3	Read & Write	Default state of output 3
196	195	0x0C3	Default state of output 4	Read & Write	Default state of output 4
817	816	0x330	Output 1	Read & Write	Output 1 state
818	817	0x331	Output 2	Read & Write	Output 2 state
819	818	0x332	Output 3	Read & Write	Output 3 state
820	819	0x333	Output 4	Read & Write	Output 4 state

## SFAR

# Mini Modbus 4DO

User Manual

#### 8. Configuration software

Modbus Configurator is software that is designed to set the module registers responsible for communication over Modbus network as well as to read and write the current value of other registers of the module. This program can be a convenient way to test the system as well as to observe real-time changes in the registers.

Communication with the module is done via the USB cable. The module does not require any drivers.



Configurator is a universal program, whereby it is possible to configure all available modules.

Stan wejść I Icznikáw     Stan wejść I Icznika   Przechwycona watość   Przechwyć   Status   Konfiguracja Icznika     Ucznik 1   290330   0   Image: Status   Konfiguracja Icznika     Ucznik 1   290330   0   Image: Status   Konfiguracja Icznika     Ucznik 1   290330   0   Image: Status   Konfiguracja Icznika     Ucznik 2   101614   0   Image: Status   Konfiguracja Icznika     Ucznik 3   0   0   Image: Status   Konfiguracja Icznika     Ucznik 4   0   0   Image: Status   Konfiguracja Icznika     Ucznik 5   0   0   Image: Status   Konfiguracja Icznika     Ucznik 6   0   0   Image: Status   Konfiguracja Icznika     Ucznik 6   0   0   Image: Status   Konfiguracja Icznika     Ucznik 8   0   0   Image: Status   Konfiguracja Icznika     Ucznik 8   0   0   Image: Status   Konfiguracja Icznika     Iucznik 8   0   0   Image: Status   Konfiguracja Icznika     Status 7   0   0   Ima	ansmisja	Moduł 8180 Modu	il 161 Modul 160 Info			
Stan wejść   Image: Stan kie znika i kantigunacja kie znikantigunacja kie znika i kantigunacja kie zni	Konfigura	cja wejść i liczników				
Stan licznika     Przechwycona watość     Przechwyć     Status     Konfiguracja licznika       Ucznik 1     290330     0		Stan wejść 🔲 🔲				
Jacamezina   Przechnycona walość   Przechnycona walość   Przechnycona walość     Licznik 1   290330   0   0   Konfiguruj     Licznik 2   101614   0   0   Konfiguruj     Licznik 3   0   0   Konfiguruj   Konfiguruj     Licznik 3   0   0   Konfiguruj   Konfiguruj     Licznik 5   0   0   Konfiguruj   Konfiguruj     Licznik 6   0   0   Konfiguruj   Konfiguruj     Licznik 7   0   0   Konfiguruj   Konfiguruj     Licznik 8   0   0   Konfiguruj   Konfiguruj     Licznik 8   0   0   Konfiguruj   Konfiguruj     Licznik 8   0   0   Konfiguruj   Konfiguruj     Konfiguruj Stan wyjść   Xan wyjść   Xan wyjść   Xan wyjść     Kan Konfiguruj Stan wyjść   Xan Wyjść   Xan Wyjść   Xan Wyjść		Que temites	Przesłuwana wstałó	Praeshuará	Chatura	Kaofia wasia kazaka
Licznk 2   101614   0   Image: Constraint of the state of the sta	Lieznik	1 290330				Konfigurati
Ucarik 3 0 0 0 Konfigunuj   Ucarik 4 0 0 0 Konfigunuj   Ucarik 4 0 0 0 Konfigunuj   Ucarik 5 0 0 0 Konfigunuj   Ucarik 6 0 0 0 Konfigunuj   Ucarik 7 0 0 Konfigunuj   Ucarik 8 0 0 Konfigunuj   Varik 8 0 0 Konfigunuj   Konfigunuj 0 0 Konfigunuj   Konfigunuj 0 0 Konfigunuj   Konfigunuj 0 0 Konfigunuj   Konfigunuj 0 0 Konfigunuj	Liezoik	2 101614				Kenfigunai
Ucznik 8   0   0   0   Kornigunuj     Ucznik 5   0   0   0   Kornigunuj     Ucznik 5   0   0   0   Kornigunuj     Ucznik 6   0   0   0   Kornigunuj     Ucznik 6   0   0   Complexity   Kornigunuj     Ucznik 7   0   0   Complexity   Kornigunuj     Ucznik 8   0   0   Complexity   Kornigunuj     Sonnyśść   2   2   2   Kornigunuj     Kornigunuj Stan wyjść   2   2   2   2     Watchdog   0   2   2   2   2	Liezeik	2 0				Konliguitij
ucznik 6   v   v   v   konfiguruj     ucznik 5   0   0   c   Konfiguruj     ucznik 6   0   0   c   Konfiguruj     ucznik 7   0   0   c   Konfiguruj     ucznik 8   0   0   c   Konfiguruj     úcznik 8   0   0   c   Konfiguruj     Konfiguruj   V   V   V   V     Stan wyjść   V   V   V   V     Vomyślny stan wyjść   V   V   V   V     Watchdog   0   V   V   V   V	Ucznik	. [0		-		Konfiguruj
ucznik 6 0 0 Konfiguruj   ucznik 6 0 0 Konfiguruj   ucznik 7 0 0 Konfiguruj   ucznik 8 0 0 Konfiguruj   úcznik 9 0 0 Konfiguruj	Ucznik	4 U				Kontiguruj
Lucznik 6 10 10 10 10 10 10 10 10 10 10 10 10 10	Ucznik					Kontiguruj
Licznik 7 0 0 0 Konfiguruj Licznik 8 0 0 Konfiguruj Konfiguracja wyjść Stan wyjść 12 12 12 12 12 12 12 12 12 12 12 12 12	Licznik	6 0				Konfiguruj
Licznik 8 0 0 Konfiguruj Konfiguracja wyjść Stan wyjść 12 12 12 12 12 12 12 12 12 12 12 12 12	Licznik	7 0				Konfiguruj
Konfiguracja wyjść Stan wyjść 🖌 🖌 🖌 🖌 🗌 📄 😾 Domyślny stan wyjść 📄 🕞 🖉 📄 📄 😾 🖉 Watchdog 🛛	Licznik	8 0	0			Konfiguruj
Stan wysec wol wol wol wol wol wol wol wol wol Domyślny stan wyśść 🗌 🗋 😡 📄 📄 😡 😡 Watchdog 🛛	Konfigura	icja wyjść		-		
Vomyślny stan wyść U U W U U U W W Watchdog 0		Stan wyjsc 🗹 🗹		N		
Watchdog 0	Domyślny	stan wyjść 🔲 🛄		M		
		Watchdog 0				

Expansion Module- 4 digital outputs

#### **User Manual**

# Table of content

1.	Safety rules	3
2.	Module Features	3
	2.1. Purpose and description of the module	3
	2.2. Technical Specifications	4
	2.3. Dimensions of the product	5
3.	Communication configuration	5
	3.1. Grounding and shielding	5
	3.2. Network Termination	5
	3.3. Types of Modbus Registers	6
	3.4. Communication settings	6
	3.4.1. Default settings	6
	3.4.2. Configuration registers	7
4.	Indicators	7
5.	Block diagram	8
6.	Module Connection	8
7.	Modules Registers	9
	7.1. Registered access	9
	7.2. Bit access	9
8.	Configuration software	10



Manufactured for: Aspar s.c. ul. Kapitańska 9 81-331 Gdynia Poland

ampero@ampero.eu www.ampero.eu Tel. +48 58 351 39 89; +48 58 732 71 73

